



# Dual S-Band Block Frequency Converters STAN Class



Dual S-Band converter with phase tracking and matching  
**FCB200-STAN Class**  
 Satellite Tracking and Navigation

## Features

- Dual L to S or Dual S to L block converters in single 1RU
- Coherent Phase tracking between each channel over time
- Gain tracking between channels
- Phase matching between channels
- Low Phase Noise
- Low Spurious levels
- Independent Input and Output attenuators
- Internal/External 10 MHz with Autosensing
- Front panel control (local)
- Input / Output Monitoring ports for each channel
- Full remote control (remote) via Ethernet with SNMP V1

## Overview

The Advantech **STAN** series of converters are designed for specific applications that require dual channel, coherent signal processing as applicable to TT&C and LEO Satellite Tracking and Navigation (STAN). Each 1RU shelf includes two independent Up (or Down) Block converters that are coherent in phase, and phase matched.

These new frequency converters use the latest technology in RF conversion, with outstanding performance in spectrum purity.

Independent Input and Output attenuators allow maximum flexibility in adjusting levels on each channel, as the application requires. Sample ports are available for each channel, on both Input and Output ports.

The flexible and comprehensive monitor and control features on the **STAN** converter ensure that it will fit into any network management system architecture. The user-friendly front panel or the Ethernet interface will provide full set-up and fault monitoring facilities.

The PLL oscillator used in the converter is either locked to a highly stable internal 10 MHz reference or if the external reference option is fitted and the proper level of signal is present, the PLL will automatically lock to the external reference.

## Operating Bands

Up-Converters			
Model Number	Type	Input Frequency	Output Frequency
ARUD-LS-STAN	dual	1.05-2.05 GHz	2.75-3.75 GHz

Down-Converters			
Model Number	Type	Input Frequency	Output Frequency
ARDD-SL-STAN	dual	2.2-2.3 GHz	1.5 - 1.6 GHz Non-inverted

## Application

The **STAN** series of S-Band converters is particularly suited for use in applications that require phase coherent signal processing, TT&C and new LEO Satellite Tracking and Navigation.

The **STAN** range of converters provides an industry leading MTBF of over 120,000 hours.

## Options

- Rack Mount set of slides  
 Note: Consult factory for detailed configuration



## S-Band Dual Block Frequency Converter STAN Class

Technical Specifications			
Up-Converter		Down-Converter	
<b>IF Input</b>		<b>RF Input</b>	
Frequency range	1.05-2.05 GHz	Frequency range	2.2-2.3 GHz
Input Connector	SMA (female) 50 Ohm	Input Connector	SMA (female) 50 Ohm
Return loss	18 dB	Return loss	18 dB
<b>RF Output</b>		<b>IF Output</b>	
Output power (P1dB)	+13 dBm	Output power (P1dB)	+18 dBm
Frequency range	2.75-3.75 GHz	Frequency range	1500-1600 MHz
IMD3 (two tone)	-50 dBc max @ 0 dBm each carrier	IMD3 (two tone)	-50 dBc max @ 0 dBm output each carrier
Output connector	SMA (female)	Output connector	SMA (female)
Connector Impedance	50 Ω	Connector Impedance	50 Ω
Return loss	18 dB	Return loss	18 dB
Transfer Characteristics		Transfer Characteristics	
Conversion Gain	30 +/- 3 dB @ max gain setting	Conversion Gain	35 +/- 3 dB @ max gain setting
Gain adjustment Output and Input	30 dB at Output ; 15 dB at Input	Gain adjustment	30 dB at Output ; 15 dB at Input
Attenuator step size	0.2 dB	Attenuator step size	0.2 dB
Gain flatness	±1.0 dB p-p over any 500 MHz	Gain flatness	±1.0 dB p-p over 100 MHz
	0.5 dB p-p over 40 MHz		0.5 dB p-p over 40 MHz
Gain stability	±0.25 dB max. /24 hours	Gain stability	±0.25 dB max. / 24 hours
	±1 dB over temp. range		±1 dB over temp. range
Channel to Channel gain tracking	±0.5 dB at constant temperature	Channel to Channel gain tracking	±1 dB at constant temperature
Channel to Channel Isolation	50 dB	Channel to Channel Isolation	50 dB
Spurious	<-65 dBc signal related @ dBm <-75 dBm signal independent	Spurious	<-65 dBc signal related@ Pout = 0dBm <-75 dBm signal independent
Image rejection	60 dB	Image rejection	60 dB
LO Leakage	< -80 dBm		
Noise Figure	16 dB	Noise Figure	15 dB
Channel to Channel Phase Tracking	+/- 2 degrees/day at constant temperature, same attenuation	Channel to Channel Phase Tracking	+/- 2 degrees/day at constant temperature, same attenuation
Channel to Channel Phase matching	+/-10 degrees	Channel to Channel Phase matching	+/-10 degrees
Phase noise	--52 dBc/Hz @ 10Hz	Phase noise	-52 dBc/Hz @ 10Hz
	-80 dBc/Hz @ 100Hz		-80 dBc/Hz @ 100Hz
	-90 dBc/Hz @ 1kHz		-90 dBc/Hz @ 1kHz
	-100 dBc/Hz @ 10kHz		-100 dBc/Hz @ 10kHz
	-110 dBc/Hz @ 100KHz		-110 dBc/Hz @ 100KHz
	-125 dBc/Hz @ 1 MHz		-125 dBc/Hz @ 1 MHz
Reference		Mechanical	
External Reference input	10 MHz, 7 +/- 3 dBm, high purity	Dimensions	Width 19" (482.6 mm)
Internal reference stability	± 1 x 10 <sup>-7</sup> over 0°C to +50°C		Height 1U 1.75" (44.5 mm)
Aging	± 5 x 10 <sup>-9</sup> / day ± 5 x 10 <sup>-8</sup> / year		Depth 22" (558.8 mm)
Environmental		Power Supply	
Operational	0°C to +50°C standard	Voltage	83 – 264 VAC (43 – 67 Hz)
Storage	-55°C to +85°C	Power	45W (typical)
Humidity	95% Non-condensing	Connector	IEC 603320 10A
Altitude	3,000m AMSL		
		Monitor and Control	
		Input Sample Port	SMA (female)
		Output Sample Port	SMA (female)
		Ethernet	RJ45 F

Request A Quote