



70/140 MHz to L-Band and L-Band to 70/140 MHz Up & Down Converter in Single 1RU Chassis



FCS500UD Series

Features

- Dual channel
- Two converters (up&down) embedded in a single 1RU chassis
- 70 MHz or 140 MHz IF
- 125 kHz step size
- Cost effective solution
- 950 – 1750 MHz or 950 – 2150 MHz L-Band
- Fully compliant with IESS 308/309 requirements
- Internal/External 10 MHz Reference with Autosensing
- High linearity
- Low group delay
- Front panel control (local) via buttons, display and LEDs
- Full remote control via RS232, RS485 or optional Ethernet interface port
- Embedded down-converter with inverted or non-inverted output spectrum available

Operating Bands

Up & Down Converters (non-inverting up, non-inverting/inverting down)			
Model Number	Type	IF & RF Inputs	RF & IF Outputs
ARMT-70L	Up & Down	70 ± 18 MHz & 950 – 1750 MHz	950 – 1750 MHz & 70 ± 18 MHz
ARMT-70LX	Up & Down	70 ± 20 MHz & 950 – 2150 MHz	950 – 2150 MHz & 70 ± 20 MHz
ARMT-140L	Up & Down	140 ± 36 MHz & 950 – 1750 MHz	950 – 1750 MHz & 140 ± 36 MHz
ARMT-140LX	Up & Down	140 ± 40 MHz & 950 – 2150 MHz	950 – 2150 MHz & 140 ± 40 MHz

Overview

Advantech Wireless dual channel converters uses the latest technology in conversion, giving two independent conversion chains in 1 RU package, local and remote control thus providing the ultimate in performance and user friendly operation at a very competitive price.

The spectral purity, low phase noise and stability exceed the requirements of all major international satellite network operators.

The flexible and comprehensive monitor and control features on the HP converter ensure that it will fit into any network management system architecture. The user-friendly front panel or the RS485 remote interface will provide full set-up and fault monitoring facilities. The RS232 will provide the Monitor and Control functions via a PC and will also allow for software downloading.

The converter is fully synthesized with the PLL oscillator either locked to a highly stable internal 10 MHz reference or if the external 10 MHz reference signal with proper power level is present, the PLL will automatically lock to the external reference.

Options

- Ethernet port and SNMP Interface
- Redundant Ready for 1:N (N=1..12)
- Rack mount set of slides
- BUC power supply 24VDC@4A or 48 VDC@2A
- LNB power supply

Application

The HP range of converters is particularly suited for use in VSAT, SCPC Networks, SNG, DVB-RCS and Hub systems. This makes them an ideal choice for large earth stations requiring cost effective solutions for frequency conversion. The lightweight, rugged and compact design also ensures that the HP converter provides the ideal solution for mobile truck or flyaway DSNG systems. With fully welded aluminum chassis and robust modular internal construction the converter can even meet the demands of military installations. The HP range of converters provides an industry leading MTBF of over 120,000 hours.



70/140 MHz to L-Band and L-Band to 70/140 MHz Up & Down Converter in Single 1RU Chassis

Technical Specifications			
Up-Converter		Down-Converter	
IF Input		RF Input	
Frequency range	(See table on front page)	Frequency range	(See table on front page)
Impedance	50 Ω standard (optional 75 Ω)	Impedance	50 Ω
Input Connector	BNC (f) <i>other options available</i>	Input Connector	Type N (f) <i>other options available</i>
Return loss	18 dB	Return loss	16 dB
RF Output		IF Output	
Frequency range	(See table on front page)	Frequency range	(See table on front page)
Output power (P1dB)	+5 dBm (optional +10 dBm)	Output power (P1dB)	+5 dBm (optional +10 dBm)
IMD3 (two tone)	-40 dBc max @ -5 dBm output	Output Connector	BNC (f) <i>other options available</i>
Output connector	Type N (f) <i>other options available</i>	Connector Impedance	50 Ω (optional 75 Ω)
Connector Impedance	50 Ω	Return Loss	18 dB
Return loss	16 dB		
Transfer Characteristics		Transfer Characteristics	
Conversion Gain	20 dB @ max gain setting	Conversion Gain	30 dB min @ max gain setting
Gain adjustment	20 dB (0.1 dB step size)	Gain adjustment	20 dB (0.1 dB step size)
Gain flatness	1.5 dB p-p max. 40 MHz 2.0 dB p-p max. 80 MHz	Gain flatness	1.5 dB p-p max. 40 MHz 2.0 dB p-p max. 80 MHz
Gain stability	± 0.25 dB max. /24 hours ± 1 dB over temp. range	Gain stability	± 0.25 dB max. / 24 hours ± 1 dB over temp. range
Spurious	-55 dBc carrier related @ -5 dBm < -60 dBm non-carrier related	Spurious	-55 dBc @ -10 dBm output
Group delay (over 40 MHz)	10 -15 ns p-p	Group delay (over 40 MHz)	10 -15 ns p-p
Group delay (with optional group delay equalizer)	Linear 0.03 ns/MHz Parabolic 0.01 ns/MHz ² Ripple 1 ns p-p	Group delay (with optional group delay equalizer)	Linear 0.03 ns/MHz Parabolic 0.01 ns/MHz ² Ripple 1 ns p-p
		Image rejection	50 dB
		Noise Figure	20 dB
Phase noise	Meets or Exceeds IESS 308/309	Phase noise	Meets or Exceeds IESS 308/309
Synthesizer step size	125k kHz	Synthesizer step size	125 kHz
Reference		Mechanical	
External Reference Freq.	10 MHz \pm 2 Hz, 0 \pm 3 dBm	Dimensions	Width 19" (482.6 mm)
External Reference Input	BNC (f) <i>other options available</i>		Height 1U 1.75" (44.5 mm)
Internal reference stability	$\pm 2 \times 10^{-10}$ / day		Depth 22" (558.8 mm)
Aging	$\pm 5 \times 10^{-8}$ / year	Cooling	Forced-Air
Environmental		Power Supply	
Operational	0°C to +50°C standard	Voltage	90 – 265 VAC (47 – 63 Hz)
Storage	-55°C to +85°C	Power	40W (typical, single converter)
Humidity	Non-condensing	Connector	IEC 603320 10A
Altitude	3,000m AMSL		
Other options		Monitor and Control	
1) 24V (4A) or 48V (2A) supply to BUC		RS 485	DB9
2) 20V supply to LNB		RS 232	DB9
3) 10 MHz reference for the BUC or LNB		Discrete	DB9
4) Rack mount set of slides		Ethernet (optional)	RJ45 F (optional)
		Buttons, display & LEDs	via Front Panel

Request A Quote