

CRS-300 1:10 Modem Redundancy Switch

Modem Accessories



Overview

The CRS-300 1:10 Modem Redundancy Switch provides fully automatic or manual redundancy for the following modems:

CDM-570A & CDM-570AL	CDM-625 & CDM-625A	CDM-700
CDM-570 & CDM-570L	CDM-Qx & CDM-QxL	CDM-710
CDM-600 & CDM-600L	SLM-5650A	CDM-710G

The protection system consists of a maximum of 10 traffic modems, a redundant modem, and the CRS-300 redundancy switch. Two companion (slaved) 1:10 switches are also available: the CRS-280/ 280L IF switch and the CRS-350 ESC switch. The IF switch is used in multiple transponder applications. The CRS-350 is used for open network ESC redundancy switching.

Compatibility

The CRS-300 supports a wide range of terrestrial data interface types including: EIA-422/530, V.35, EIA-232, LVDS, G.703 (balanced or unbalanced), ASI, 10/100/1000 Ethernet and HSSI. In many cases, each traffic modem can have a different terrestrial data interface types.

Key Features

- Twin, independent AC or DC power supplies
- Passive backplane for signal path
- Non-interruption of normal traffic upon power failure
- Non-interruption of user data when other traffic modem Interface circuit cards are removed
- Data and clock provided to the redundant modem when in Bridge Mode
- Programmable holdoff times to backup or restore
- Audible alarm programmable to activate, based on various changes in status
- Provides single-point remote Monitor and Control (M&C) to switch and traffic modems
- Simplified configuration and control
- 2 line x 24 character vacuum fluorescent display
- Front panel keypad
- LED system status display showing unit and modem status, online/offline status, and bridge status

Superior Functionality

The configuration of each traffic modem is stored in the CRS-300 controller. This information is used to program the redundant modem if the traffic modem fails. The modem information is copied to the controller through a serial cable. The CRS-300 also controls the traffic and redundant modem IF output. All modem outputs are ON if the CRS-280 or CRS-280L IF switch is used in the system. The downlink path through the CRS-280/ CRS-280L is completely passive. External monitor and control may be connected to the CRS-230 controller board. The CRS-300 and each traffic modem may be monitored or controlled through this remote serial interface.

The data and clock signals to and from a traffic modem are routed through a Traffic Modem Interface (TMI) via a set of relays. This allows the data signals to pass directly through to the traffic modem in the event of a power failure. If the system's power supplies are lost, or if a TMI carrying traffic is removed, no interruption of traffic occurs. The Bridge Mode may be used to verify the user data on a specific traffic modem. The redundant modem locks to the traffic modem receive IF input signal. The operator can program a delay interval for the backup modem to wait before coming online when a traffic modem failure occurs.

Modular Construction

The redundancy switches are modular in construction. All replaceable modules insert into slots in the back panel, including the controller, TMIs, Redundant Modem Interfaces (RMIs), and Power Supply Units (PSUs). Power consumption is so low, even for fully populated units that no fan cooling is required.

Specifications

Type	1:10 Redundancy Switch system, N=10 max., bridging architecture
Operating Modes	Fully automatic or manual Force traffic modem to redundant modem Remove selected traffic modem from control Programmable hold-off to backup and hold – off to restore (from 2 to 99 seconds)
Switching Conditions	Switch to redundant modem following a unit fault TX traffic alarm or RX traffic alarm
IF Switching	With CRS-280 IF Switch; all modems outputs on all the time Without CRS-280 IF Switch: IF on/off control to modems
Redundant Modem Signal Source	Any one of the 10 traffic paths (bridge mode) (both RX IF and TX data)
Front Panel	Vacuum fluorescent display, 2 lines, 24 characters LED status display showing, for all modems Unit status, TX status, RX status, online and bridge status
Audible Alarm	Programmable to activate following various changes of state
Common faults	Dry relay contacts
Prime Power	Two independent inputs, (AC or DC versions available): 90 to 264 VAC, 50/60 Hz, or 48 (38 to 60) VDC < 25 W
Dimensions (Rack Mount – 4RU) (height x width x depth)	6.75" x 19" x 11.75" (17.15 x 48.26 x 29.85 cm)
Weight	~ 20 lbs (~ 9.07 kg)
Temperature	0 to +50°C (32 to 122°F) operating 50 to 100°C (122 to 212°F) storage
Humidity	95% at +40°C (104°F), non-condensing
CE Mark	EMC and Safety

CRS-280/280L – IF Switch (optional)

	CRS-280 (70/140 MHz)	CRS-280L (L-Band)
Operating Frequency	50 to 180 MHz	950 to 1950 MHz
Connector Type	TX/RX BNC or TNC	TX/RX N-type
Return Loss	18 dB into 75 Ω	15 dB into 50 Ω
Power	From CRS-300	100-240 VAC 50/60 Hz (25 W) 36-60 VDC (25 W)
Dimensions (Rack Mount – 4 U) (height x width x depth)	7" x 19" x 2.5" (18 x 48.26 x 6.35 cm)	7" x 19" x 14" (18 x 48.26 x 36 cm)
Weight	< 10 lbs (< 4.54 kg)	< 25 lbs (11.3 kg)

Modem vs Terrestrial User Data Interface

Modem	TMI	User Data Type	User Data Connector(s)
CDM-570A	CRS-320	EIA-422, V.35, EIA-232	(1) DB-25F
CDM-570AL	CRS-330	G.703 (balanced/unbalanced)	(1) DB-15F/ (2) BNC
CDM-570	CRS-340	EIA-422, V.35, RS-232	(1) DB-25F
CDM-570L		G.703 (balanced/unbalanced)	(1) DB-15F/ (2) BNC

CDM-600 CDM-600L	CRS-320	EIA-422, V.35, RS-232	(1) DB-25F	
	CRS-330	G.703 bal. (DDI,IDO, DDO, IDI) G.703 unbal. (DDI, IDO, DDO, IDI)	(1) DB-15F (4) BNC	
	CRS-340	EIA-422, V.35, RS-232, LVDS G.703 bal. (DDI,IDO, DDO, IDI) G.703 unbal. (DDI, IDO)	(1) DB-25F (1) DB-15F (2) BNC	
CDM-625 CDM-625A	CRS-370	HSSI (User)	(1) HD-50F	
	CRS-316	EIA-422, V.35 1 port of 10/100 Ethernet (bridge mode)	(1) DB-25F (1) RJ-45	
	CRS-325	ASI	(2) BNC	
	CRS-330	G.703 bal. (DDI,IDO, DDO, IDI) G.703 unbal. (DDI, IDO, DDO, IDI)	(1) DB-15F (4) BNC	
	CRS-336	HSSI or Bridge Ethernet	(1) HD-50F (1) RJ-45	
	CRS-340	EIA-422, V.35, LVDS G.703 bal. (DDI,IDO, DDO, IDI) G.703 unbal. (DDI, IDO)	(1) DB-25F (1) DB-15F (2) BNC	
	CRS-365D	Quad E1 (1 to 4 Ports of E1)	(2) DB-9F	
	CDM-Qx CDM-QxL	CRS-316	EIA-530, V.35, EIA-232	(1) DB-25F
		CRS-325	G.703 bal. (DDI,IDO, DDO, IDI) G.703 unbal. (DDI, IDO)	(1) DB-15F (2) BNCs
		CRS-336	HSSI	(1) HD-50F
CDM-700	CRS-365	Quad E1 (1 to 4 Ports of E1)	(4) RJ-45s	
	CRS-325	OC3 copper	(2) BNCs	
	CRS-336	HSSI GigE	(1) HD-50F (1) RJ-45	
CDM-710	CRS-345	Multi-port unbal. G.703 (1-4 ports)	(8) BNCs	
	CRS-325	ASI	(2) BNCs	
CDM-710G	CRS-336	HSSI GigE	(1) HD-50F (1) RJ-45	
	CRS-325	Unbalanced G.703	(2) BNCs	
	CRS-336	HSSI GigE	(1) HD-50F (1) RJ-45	
SLM-5650A	CRS-316	MIL-STD-188-114, EIA-530 GigE	(1) DB-25F (1) RJ-45	
	CRS-325	G.703 bal. (DDI,IDO, DDO, IDI) G.703 unbal. (DDI, IDO)	(1) DB-15F (2) BNCs	
	CRS-336	HSSI GigE	(1) HD-50F (1) RJ-45	
	CRS-336	HSSI GigE	(1) HD-50F (1) RJ-45	

Notes:

1. SLM-5650 (non "A" version) see Legacy 1:10 Switch Datasheet

CRS-350 – Engineering Service Channel Switch (optional)

Applicable Modems	CDM-600/600L/625, SLM-5650A
User Data Interfaces	(1) DB-25M connector - ESC, overhead signals (1) DB-15F connector - IDR alarms (1) DB-9F connector - audio
Power	From CRS-300
Dimensions (Rack Mount – 4U) (height x width x depth)	7" x 19" x 4.0" (18 x 48.26 x 27.5 cm)
Weight	5 lbs (2.2 kg)



CRS-280



CRS-280L



CRS-350

Request A Quote